



BLUEPIRAT

BY MAGNA



BLUEPIRAT Series Cellular Network User Guide / 21.07.2020

Version 3.4.3

Table of contents

1	LICENSE AGREEMENT	3
2	PRODUCT LIABILITY	4
3	Overview.....	5
4	System requirements	7
4.1	Further manuals.....	8
4.2	Additional features by optional licenses	9
4.3	Firmware Care	10
5	Configuration	11
5.1	Entering a recipient.....	11
5.2	Inserting text or elements.....	12
5.2.1	Inserting CAN / LIN / FlexRay signals.....	13
5.2.2	Inserting GPS signals	14
5.2.3	Inserting logger signals.....	14
5.2.4	Inserting digital / analog signals.....	16
5.2.5	Status messages of the logger	16
6	Abbreviations.....	17
7	List of figures	19
8	List of tables	20
9	Version history.....	21
10	Contact	22

1 LICENSE AGREEMENT

Please read the license agreement of this license contract carefully, before you install the software. By the installation of the software you agree to the conditions of this license contract.

This software-license agreement, in the following called "license", contains all rights and restrictions for final users that regulate the use of the accompanying software, operating instructions and other documents, in the following called as "software".

1. This license contract is an agreement between licensor and licensee, who is being licensed to use the named software.
2. Licensee acknowledges that this is only a limited nonexclusive license. This means, that the licensee has no right to allocate sublicenses. Licensor is and remains the owner of all titles, rights and interests in the software.
3. The software is a copyright property of the MAGNA Telemotive GmbH. The program or parts of it may not be further licensed to third parts, rented, sold or be further marketed in any form without explicit written approval by MAGNA Telemotive GmbH. The user may neither change the software and their components, nor modify, nor redevelop or decompile otherwise in any form.
4. This software is subject to no warranty. This software is sold as is, without any warranty. If at any time, a user changes his system, we hold no responsibility to change our software to make it work again.
5. This license permits licensee to install the software on more than one computer system, as long as the software will not be used on more than one computer system simultaneously. Licensee will not make copies of the software or allow copies of the software to be made by others, unless authorized by this license agreement. Licensee may make copies of the software for backup purposes only. Licensee is not entitled to transmit or to transfer the software or its rights from this license agreement.
6. Licensor is not liable to licensee for any damages, including compensatory, special, incidental, exemplary, punitive or consequential damages, connected with or resulting from this license agreement or licensee's use of this software.
7. Licensee agrees to defend and indemnify licensor and hold licensor harmless from all claims, losses, damages, complaints or expenses connected with or resulting from licensee's business operations.
8. Licensor has the right to terminate this license agreement and licensee's right to use this software upon any material breach by licensee. The duration of the license contract is indefinitely determined.
9. Licensee agrees to return all copies of the software to licensor or to destroy them upon termination of the license contract.
10. This license agreement replaces and supersedes all prior negotiations, dealings and agreements between licensor and licensee regarding this software.
11. This license contract is subject to German law.
12. If a regulation of this license contract is void by law, the validity of the remaining regulations is not affected. If there is such a regulation it will be replaced by a valid, according to the legal regulations and enforceable regulation with similar intention and similar economic consequence.
13. The license contract is effective by delivery of the software of the licensor to the licensee and/or by usage of the software by the licensee. This license contract is also valid without licensor's signature.
14. The license automatically goes out if the licensee does not agree to the license regulations described here or offend against the license regulations of this license contract. With ending the license contract the licensee is obliged to extinguish or to destroy the software and all copies of it no matter if installed or stored on disk or to hand all of it back to MAGNA Telemotive GmbH.
15. The licensee is liable for all damages caused to the licensor by the violation of these license regulations.

2 PRODUCT LIABILITY

The General Terms and Conditions of Sale and Delivery of MAGNA Telemotive GmbH can be found on our website (<https://telemotive.magna.com>) under imprint.

3 Overview

This user guide describes the feature of the license **Cellular Network** for the data loggers

- BLUEPIRAT2
- BLUEPIRAT2 5E
- BLUEPIRAT Mini
- BLUEPIRAT Remote

of MAGNA Telemotive GmbH.

This user guide describes the configuration and usage of this feature. The general configuration is described in the user guides of the used data logger as well as the System Client, which is valid together.

This document refers to **firmware version 03.04.03** and the **System Client** from **version 3.4.3**. Some features depending on model and feature license or may not be available in older versions.

Software updates and user guides for other, optional, licensed enhancements are available in our ServiceCenter. (Please find the address under Contact at the last page.)

To ensure the most reliable operation of your system as possible, please make sure to use always current firmware and software versions.

Current supported UMTS sticks:

- 4G Systems | XS Stick P14

Current supported mobile networks

- Vodafone.de
- Telekom.de

Note:

The PIN of the SIM card must be deactivated mandatory. When pluggin in the device the XS manager will be installed automatically which offers the possibility for removing the pin. A manual is enclosed to the stick.

Note:

Please take care that the UMTS stick is connected directly to the logger and not to a interconnected HUB.

Please note these important instructions about the handling of devices of MAGNA Telemotive GmbH!

There's a linux system running on the devices and sometimes when the device has a dirty shutdown due to a power break down or unplugging the power supply, the system is corrupt from this time. You know this situation from a PC, when you switch it off some times it maybe will not work any more or show you some mistakes.

In most cases this issue is caught up and repaired by the linux system we use, but sometimes it can happen that the system on the logger is damaged and there's no access to the device any more.

We are optimizing the handling of corrupted systems permanently and are integrating some new enhancements regarding this kind of issues with every new release to save the system. But we can't make the system for 100% save against these influences.

So please use always the provided mechanism for shutting down the device or the implemented standby function in which the device shutting down when no traffic is detected any more in an adjustable time.

[Index](#)

4 System requirements

Control Unit

A Windows based Laptop or PC is needed to configure the devices by **System Client**. It also allows to save the recorded data and to use them offline later.

System Client

The software client is used for configuring the data logger as well as downloading the recorded data or convert these into your needed file format. A firmware update can be performed by the **System Client** too to ensure that your devices are always up to date.

BLUEPIRAT2 / BLUEPIRAT2 5E / BLUEPIRAT Mini

The communication between bus systems and control units is monitored and relevant data can be recorded very precisely with the data logger. The collected data are stored to the logger and can be downloaded via Ethernet to a PC.

The **BLUEPIRAT2** is our top-class all-in-one data logger. Seven models cover a wide range of interfaces.

Additionally, the **BLUEPIRAT2 5E** offers improved power management and power backup, five integrated Ethernet ports and super-fast start-up behavior. The BLUEPIRAT2 can be expanded flexibly via [System Link](#).

The **BLUEPIRAT Mini** is smallest data logger in the world with an outstanding functional scope. It offers a wide range of interfaces, stable temperature behavior, very low energy consumption, four GBit Ethernet ports, and much more. Different BLUEPIRAT Mini can be expanded flexibly to one cluster and therefore handled very easily by using [System Link](#).

Remote Control Touch (optional)

Operate your BLUEPIRAT Mini or BLUEPIRAT2 data loggers safely and comfortably from the driver's or passenger seat. Via System Link our new remote control becomes part of your logger network. One remote control can handle all connected loggers.

BLUEPIRAT Remote (optional)

While Remote Control Touch is just a control unit for handling unique devices or a TSL network, the BLUEPIRAT Remote additional has logger functionality by offering internal storage and some interfaces.

License

For some additional features an installed license is required. Settings for licensed features can be performed with a valid license only.

If you need a license for your logger, please contact our sales department (please find the address under contact at the last page).

4.1 Further manuals

Beside this user guide we offer the main manuals for our client as well as for the different data logger generations in our Service Center at <https://sc.telemotive.de/bluepirat>.

User manual for the System Client

https://sc.telemotive.de/4/uploads/media/TelemotiveSystemClient_UserManual.pdf

User manual for BLUEPIRAT2 / BLUEPIRAT2 5E

https://www.telemotive.de/4/uploads/media/blue_PiraT2_UserManual.pdf

User manual for BLUEPIRAT Mini

https://www.telemotive.de/4/uploads/media/blue_PiraT_Mini_UserManual.pdf

User manual for Remote Control Touch

https://sc.telemotive.de/4/uploads/media/RCTouch_UserGuide.pdf

User manual for BLUEPIRAT Remote

https://sc.telemotive.de/4/uploads/media/blue_PiraT_Remote_UserGuide.pdf

For having an easy access if necessary, the most important manuals are linked in the client under the menu item [Help] and are reachable easily from there.




Figure 4.1: links to the manuals

Our licensed enhancements have own manuals which are stored in the Service Center too. You will find a list of these enhancements in the user manuals in the chapter **Additional features by optional licenses**.

4.2 Additional features by optional licenses

Additional features can be activated by purchasing and installing licenses. Licenses can be ordered at our sales team. You find the user guides for these additional features in our Service Center. Currently the following licensed features are available.

Feature	Description
Camera Link	video recording via video server or network cameras
WLAN	supporting wireless LAN (802.11, 802.11a, 802.11n), (802.11ac from FW 02.04.01)
GPS logging	tracking of GPS data
Measurements with CCP	CAN Calibration Protocol
Measurements with XCP	Universal Measurement and Calibration Protocol Currently the functionality for Ethernet (XCP on Ethernet) and the CAN-bus (XCP on CAN) are available.
MOST150 Streaming	logging MOST150 synchronous/isochronous data
MLBevo	The license Connected-Gateway MLBevo enables the recording of data of the ATOP control unit MLBevo via USB to the Telemotive data logger and convert these data with the System Client. (from FW 02.03.01)
Download Terminal	Download Terminal allows an automatization of configured tasks for a defined group of devices. (from FW 02.03.01)
TPE	TPE = Telemotive Performance Extension Increasing the logging rate for Ethernet data up to 100Mbit/s (from FW 02.04.01)
Test automatisation	Interface for connecting to test automation tools. At the moment, the sending of CAN messages is supported. (from FW 02.04.01)
Cellular network	Allows the logger to send status messages over cellular network. (from FW 03.01.01)

Table 4.1: Additional features by optional licenses

4.3 Firmware Care

MAGNA Telemotive GmbH invests a great amount in the further development of its products.

For this we regularly provide new functions and enhancements via firmware and client releases.

Basic conditions

As part of the " Service Product Firmware Care ", new software and firmware versions are made available for download for a limited period of time. This service is available for 12 months from the date of purchasing the **BLUEPIRAT Rapid**. This period can be extended.

For details, please contact your sales partner (see contact at the end of the manual for addresses).

Affected products

- **BLUEPIRAT Mini**
- **BLUEPIRAT2 5E**
- **BLUEPIRAT2**
- **BLUEPIRAT Remote**
- **Remote Control Touch**
- **BLUEPIRAT Rapid**

Note:

Enhancements are only possible in current firmware releases.

Attention:

Please note that updates to main firmware versions (04.00.01 / 05.00.01) need a special update license and can't be flashed to a device without this license.

To buy these licenses please contact our sales department under TMO.Sales@magna.com (please find the complete address under Contact on the last page).

5 Configuration

The license **Cellular Network**, gives the devices the option of actively sending status messages via SMS or e-mail, thereby prompting the user promptly with feedback on events or errors. The functionality is implemented via an extension of the complex triggers.

The termination of the information on the cellular network can be initiated via all events which are possible for complex triggers too.

These events, which can be configured as triggers, are selectable as triggers for the following actions:

- Send SMS
- Send E-Mail

Attention: For reasons of cost and spam protection, an SMS or e-mail can only be sent every 60 seconds.

A detailed description about configuring the events can be found in the manual for the System Client.

(https://sc.telemotive.de/4/uploads/media/TelemotiveSystemClient_UserManual.pdf)




Figure 5.1: creating a new trigger

5.1 Entering a recipient

For sending an SMS / E-Mail, the **[Send SMS]** or **[Send E-Mail]** option must be configured as an action.




Figure 5.2: choosing the action

Figure 5.3: Entering a recipient

A recipient has to be specified at first. For sending a SMS, a valid telephone number including country code, for sending an E-Mail, a valid e-mail address must be entered.

5.2 Inserting text or elements

In the next step, the text to be sent can be entered. Here, normal text can be used or certain signals can be inserted from the logger using the **[Insert Element]** button. A total of 1500 characters (SMS) are available. For a simpler analysis, it is recommended to describe the selected elements.

E.g. For the [Logger_Status], the result is e.g. Only * OK * or * ERROR *. For a faster overview, this can be inserted with: **Logger_Status: [Logger.Status]** and then appears in the message as: **Logger_Status: OK**




Figure 5.4: Inserting elements

Note:

When sending e-mails, you can't use as many characters in the text field as via SMS. Depending on the mobile phone provider a different numbers of characters can be used (round about

566). In addition, when sending an e-mail, the recipient(s) is written to the beginning of the message and therefore has also to be subtracted from the transferable length.

Please also note, that not every mobile phone provider offers the necessary service "sms2email" (o2 for example, does not offer this service).

5.2.1 Inserting CAN / LIN / FlexRay signals

A data base must be consigned for **CAN, LIN and FlexRay** signals in order for select these signals.




Figure 5.5: Inserting CAN / LIN / FlexRay signals




Figure 5.6: Inserting elements

5.2.2 Inserting GPS signals

For inserting **GPS signals**, the available signals are listed. They can be marked and accepted via **[OK]**.




Figure 5.7: Inserting GPS signals

5.2.3 Inserting logger signals

In the same way you can select directly **logger signals**.




Figure 5.8: Inserting logger signals

The following signals are available for the logger status:

Signalname	Type	Description
Logger.Status	„ok“ „warning“ „mem“ „ring“ „error“	No incidents There are warnings Internal memory is full, logging is stopped Ring buffer is full, old traces are deleted Logger in fault condition
Logger.IntMemory	Double (0..100)	Fill level of the internal memory HDD, SSD, Flash
Logger.ExtMemory	Double (0..100)	Fill level of the external Speicher CF-Flash, SD-Card
Logger.Start	Bool	Logger is started The value 1.00 indicates that the logger is started
Logger.Timer	64Bit Integer	Past time in seconds since logger start or configuration change. The counter is reset to 0 after each restart or configuration change.

Table 5.1: Logger Status Signals

Here is a sample e-mail configured in the text field of a trigger.

For these logger status messages, it is useful to have a description inserted, see below.

Text:

```

Logger Status: [Logger.Status]

Logger started: [Logger.Start]

Fill level of the internal memory: [Logger.IntMemory]

Fill level of the external memory: [Logger.ExtMemory]

Past time in seconds since logger start or configuration change: [Logger.Timer]

```

Figure 5.9: Configured logger signals in the trigger text field

E-Mail:

```

Logger: bPMini_4
S/N: 1007419
Status: Ring
Disk: 100%

```

```

Logger Status: Ring
Logger started: 1.00
Fill level of the internal memory: 100.00
Fill level of the external memory: 97.00
Past time in seconds since logger start or configuration change: 13.00

```

Figure 5.10: Content of a status message e-mail

The values of the fill level of the internal and external memory are percentages.

5.2.4 Inserting digital / analog signals

From the **Digital input**, the current status 0 or 1 will be submitted.

The input signal from the **Analog input** can be configured by the following mask:

The screenshot shows a dialog box titled "Define analog input". It has a close button (X) in the top right corner. The "Channel" dropdown is set to "Analog #1". Under the "General" section, the "Name" field contains "Voltage" and the "Unit" field contains "V". Under the "Linear conversion" section, the "Scale" field contains "1" and the "Offset" field contains "0". A hint below this section reads "Hint: f(x) = Scale * x + Offset". Under the "Display parameter" section, the "Format" dropdown is set to "Decimal" and the "Decimal places" dropdown is set to "3". At the bottom right, there are "Abort" and "Ok" buttons.

Figure 5.11: Define analog inputs

At last, the configuration must be sent to the logger and is directly active. As soon as the configured event occurs, the information is sent.

5.2.5 Status messages of the logger

For each sent SMS or e-mail, the status of the logger and the memory fill level of the internal hard disk are displayed in the header:

```

Logger: bPMini_4
S/N: 1007419
Status: OK
Disk: 15%

```


6 Abbreviations

Kürzel / abbreviation	Bedeutung / meaning
BLUEPIRAT	Processing Information Recording Analyzing Tool
bP	BLUEPIRAT
bP2	BLUEPIRAT2
bP2 5E	BLUEPIRAT2 5E
bPMini	BLUEPIRAT Mini
RC Touch	Remote Control Touch
bP Remote	BLUEPIRAT Remote
A2L	ASAM MCD-2 MC Language
AE	Automotive Electronics
ACK	ACKnowledged
CAN	Controller Area Network
CCP	CAN Calibration Protocol
CF	Compact Flash
CRO	Command Receive Object
DAQ	Data Acquisition
DTO	Data Transmission Object
ECL	Electrical Control Line
ECU	Electronic Control Unit
FIBEX	Field Bus Exchange Format
FW	Firmware
GMT	Greenwich Mean Time
INCA	INtegrated Calibration and Application Tool
LAN	Local Area Network = Netzwerk
LIN	Local Interconnect Network
MAC	M edia A ccess C ontrol
MCD	M easure C alibrate D iagnose
MDX	M eta D ata E Xchange Format
MEP	MOST Ethernet Packet
MOST	Media Oriented Systems Transport (www.mostnet.de)
ODT	O bject D escriptor T able
ODX	O pen D ata E Xchange
OEM	O riginal E quipment M anufacturer
PHY	PH ysical Bus Connect
PW	Password
RX	Receiver Data
SD	Secure Digital
SFTP	Secure File Transfer Protocol
SHA	Secure Hash
SSL	Secure Sockets Layer
TCP/IP	Transmission Control Protocol/Internet Protocol
TLS	Transport Layer Security

TMP	Telemotive Packetformat
TSA	Telemotive System Access
TSL	Telemotive System Link
UDP	User Datagram Protocol
USB	Universal Serial Bus
UTC	Universal Time, Coordinated
Wi-Fi	Wireless Fidelity
WLAN	Wireless Local Area Network
XCP	Universal Measurement and Calibration Protocol

Table 6.1: Abbreviations

7 List of figures

Figure 4.1: links to the manuals.....	8
Figure 5.1: creating a new trigger.....	11
Figure 5.2: choosing the action.....	11
Figure 5.3: Entering a recipient.....	12
Figure 5.4: Inserting elements.....	12
Figure 5.5: Inserting CAN / LIN / FlexRay signals.....	13
Figure 5.6: Inserting elements.....	13
Figure 5.7: Inserting GPS signals.....	14
Figure 5.8: Inserting logger signals.....	14
Figure 5.9: Configured logger signals in the trigger text field.....	15
Figure 5.10: Content of a status message e-mail.....	15
Figure 5.11: Define analog inputs.....	16

[Index](#)

8 List of tables

Table 4.1: Additional features by optional licenses	9
Table 5.1: Logger Status Signals.....	15
Table 6.1: Abbreviations.....	18
Table 9.1: Version history.....	21

[Index](#)

9 Version history

Version	Änderung	Datum

Table 9.1: Version history

10 Contact



DRIVING **EXCELLENCE.**
INSPIRING **INNOVATION.**

MAGNA Telemotive GmbH

Office München
Frankfurter Ring 115a
80807 München / Germany

Tel.: +49 89 357186-0
Fax.: +49 89 357186-520
E-Mail: TMO.info@magna.com
Web: <https://telemotive.magna.com>

Sales
Tel.: +49 89 357186-550
Fax.: +49 89 357186-520
E-Mail: TMO.Sales@magna.com

Support
Tel.: +49 89 357186-518
E-Mail: TMO.productsupport@magna.com
ServiceCenter: <https://sc.telemotive.de/bluepirat>

© by MAGNA Telemotive GmbH
Subject to errors and to technical changes as part of product improvement.